

Product datasheet

Specifications



TSX Micro - 8 analogue input 0-10 V

TSXAEZ801

⚠ Discontinued on: 31 Dec 2019

⚠ To be end-of-service on: 31 Dec 2027

EAN Code: 3389110604498

⚠ Discontinued

Main

Range of product	Modicon TSX Micro automation platform
Product or component type	Analog input module
Number of channels	8
Analogue input type	0...10 V

Complementary

Analog/digital conversion	11 bits + sign
Acquisition period	32 ms
Temperature drift	0.068 %/10 °C
Input impedance	2.2 Ohm
Current consumption	60 mA
Isolation voltage	1000 V AC
Net weight	0.2 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.5 cm
Package 1 Width	18.0 cm
Package 1 Length	26.0 cm
Package 1 Weight	341.0 g

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

EU RoHS Directive

Not applicable, out of EU RoHS legal scope

Use Longer



Lifetime extension

Repair

No

Connections and Schema

Wiring Diagram

